

# SMH-X

## SHOCK MOUNT HOLDER



### USER MANUAL

Thank you for purchasing the SMH-X Shock Mount Microphone Holder. It is designed to isolate your Azden shotgun microphone from handling noise and vibration. In addition to Azden brand microphones, this shock mount is compatible with many other third-party shotgun microphones. Two sizes of microphone clips are provided for a wider range of compatibility. For a list of compatible microphones, please see [azden.com](http://azden.com).

Please read your user manual carefully.



### CAUTION

- Do not use or store this product in environments that are extreme in temperature, moisture or dust.
- Do not drop or hit with force. Use with care.
- Do not store this product under heavy weight or physical stress as permanent deformation may occur.
- If dirty, wipe clean with a soft cloth. Do not use chemical cleaning agents.

### KEY FEATURES

- The clips provided with the SMH-X mount can accommodate microphones with diameters of 18 mm to 22 mm.
- The SMH-X can be mounted on top of cameras that provide a standard size accessories shoe or on tripods, boom poles, or accessory bars that provide a 1/4" - 20 size thread.


### PACKAGE CONTENTS



Small Microphone Clips (Ø 18 mm - 20 mm)



Large Microphone Clips (Ø 21 mm - 22 mm)




Mounting Base




Clip Screws

### ASSEMBLY AND MOUNTING




Select the size microphone clip that best suits your microphone. Install the clips into the mounting base using the screws as pictured.

Tighten the screws with a Phillips head screwdriver.



Once the clips are installed, your SMH-X mount is ready to be used with your microphone.



For camera mounting, slide the shoe of the SMH-X (bottom) into the shoe mount of your camera and tighten the thumb-wheel by turning it clockwise.

## AZDEN CORPORATION

[www.azden.com](http://www.azden.com)  
[e-mail:sales@azden.com](mailto:sales@azden.com)

USA Office: 200 Valley Rd, STE 101, Mt. Arlington, NJ 07856  
TEL: +1 (973) 810-30670 FAX: +1 (973) 810-30676