

SMX-10 STEREO MICROPHONE INSTRUCTION MANUAL

Thank you for purchasing the Azden SMX-10 stereo microphone. The SMX-10 is designed for videographers that require high quality stereo sound pick-up.

BATTERY:

Unscrew the lower half of the microphone by turning the case counter clockwise. Insert one AAA battery into the case. Check for correct polarity. Replace the case and turn clockwise to tighten. Do not over tighten or you may damage the threads.

PLUG-IN POWER:

The SMX-10 may also operate on "plug-in power" if provided by the connected camera's microphone input. In this case a battery is not required. However, for best performance the use of a fresh battery is recommended.

MICROPHONE HOLDER:

Snap the microphone into the holder towards the back of the case. Slide the holder onto the shoe mount of the camera and tighten the wheel until snug. Do not over tighten or you may damage the threads.

WINDSCREEN:

Slide the windscreen over the front end of the microphone and cover all the vents on the case.

OUTPUT CABLE:

Plug the microphone's output cable into the "Ext. Mic" input jack on your camera.

POWER SWITCH:

SPECIFICATIONS

Switch to "ON" for normal operation using battery power.

Switch to "OFF" to avoid draining the battery and/or to use plug-in power.

Note: The SMX-10 will continue to operate even when the power switch is turned off and/or a battery is not installed if plug-in power is provided by the microphone input jack.

LOW CUT FILTER SWITCH:

: Turn the low cut filter switch to "ON" to reduce low frequency sounds and increase clarity.

---- : Turn the low cut filter switch to "OFF" for flat response and maximum bass.

POLAR PATTERN

Type: Stereo Electret Condenser
Sensitivity: -40 dB (at 1 kHz 1 V/Pa)


Frequency Response: 100 - 20,000 HzOutput Impedance: $1.5 \text{ k}\Omega$ (at 1 kHz)


Power Source: DC 1.5 V AAA size battery

Max. SPL: 100 dB

Signal Noise Ratio: More than 60 dB

Plug Cord Assembly: Coiled cord with φ 3.5 mm plug





Register For Your 2 Year Warranty

Congratulations on your purchase of the SMX-10 Stereo Microphone. The SMX-10 is covered by a limited warranty for two (2) years from the date of original purchase by the end user. Registration is required for this warranty to be valid. Registration may be completed anytime within two years from the date of purchase. To register this product, please go online to warranty.azden.com.

Azden Two Year Limited Warranty

Azden Corporation warrants, to the first purchaser, that the Azden brand product purchased is free from defects in material and workmanship. Azden's sole obligation under this warranty shall be to provide, without charge, repair or replacement (at Azden's sole discretion), within two years from the date of purchase. A dated receipt is required to establish the date of purchase and registration is required to receive warranty service under this two year limited warranty. The cost to ship a failed product to and from Azden or to its dealer shall not be covered by this warranty.

This warranty is the sole and exclusive express warranty given with respect to the product and all other warranties, expressed or implied, are hereby excluded. Neither Azden, nor the dealer who sells this product, is responsible for indirect, incidental or consequential damages.

This warranty does not extend to any defect, malfunction or failure caused by misuse, abuse, accident, act of God, faulty hookup, unauthorized modification, connecting this product to equipment for which this product is not intended or defective associated equipment.

Full details on this warranty agreement can be found online at www.azden.com/warranty.

AZDEN CORPORATION

Head Office:

1-12-17 Kamirenjaku Mitaka-shi, Tokyo, 181-8533 Japan Tel: +81-1-422-55-5115 • Fax: +81-422-55-0131 email: sales@azden.co.jp • www.azden.co.jp

USA Office:

200 Valley Rd, Suite 101, Mt. Arlington, NJ 07856 TEL: +1 973-810-3070 • FAX: +1 973-810-3076 e-mail: sales@azden.com • www.azden.com